



Flash fixe 8 Diodes (FF8I14)

The light alarm center is compatible with all Jenile products. It is a tailor-made tool allowing its user to differentiate two identical emitters on two separate diodes. The user can choose to connect a transmitter to any diode. A diode can receive up to 20 transmitters.

Technical Specifications

Height	15 cm	Wireless device	No
Width	8,1 cm	Decoding format	MCU
Depth	2.5 cm (bottom) 5.3 cm (top)	Guarantee	2 years
Weight	138g	Quantity of connected products	20 units maximum
Alimentation	12V 1A AC / DC adapter	Radio wave reception distance	250m in free field maximum

Contents

1x Flash 8 Fixed Diodes

1x Power cable

